

AdminCenter Account for the vPBX Administrator

Introduction

Here the AdminCenter Login of the vPBX administrator is managed and configured:

- ◇ User name and password
- ◇ Language used the AdminCenter GUI
- ◇ Email address where instructions can be send for recovering the login if the current login credential are lost or forgotten
- ◇ Define if the password has to be renewed upon the first access by the user
- ◇ Unblock a blocked account
- ◇ Defining from which IP subnet a user is allowed to access its AdminCenter account
- ◇ Defining an Access Profile which contains a list allowed IP subnets where IP subnet a user is allowed to access its AdminCenter account

Contents

- 1 The AdminCenter Account for the vPBX Administrator
 - ◆ 1.1 The Login Credentials of the vPBX Administrator
 - ◆ 1.2 Procedure in Case of Loss of the Login Credentials
 - ◆ 1.3 Used Language in the AdminCenter GUI
 - ◆ 1.4 Renew the Password Upon First Access
 - ◆ 1.5 Unblock an AdminCenter Account
- 2 Limitation of the IP Subnet for the AdminCenter Access
 - ◆ 2.1 Limitation of the IP Subnet for the Access
 - ◆ 2.2 Limitation of the IP Subnets with an Access Profile
- 3 Configuration
 - ◆ 3.1 Where to Configure this Feature
 - ◆ 3.2 Parameter Configuration
 - ◇ 3.2.1 Parameter: Username
 - ◇ 3.2.2 Parameter: Current password
 - ◇ 3.2.3 Parameter: New Password
 - ◇ 3.2.4 Parameter: Confirm new password
 - ◇ 3.2.5 Parameter: Username
 - ◇ 3.2.6 Parameter: Password
 - ◇ 3.2.7 Parameter: Renew Password
 - ◇ 3.2.8 Parameter: Language
 - ◇ 3.2.9 Parameter: Email

The AdminCenter Account for the vPBX Administrator

The Login Credentials of the vPBX Administrator

The vPBX administrator can configure the password for its AdminCenter user account. The username can only be changed by the system administrator/operator of the provider.

An email address can be configured where instructions will be sent for recovering the login.

Procedure in Case of Loss of the Login Credentials

If login details are lost then the following procedures are possible for regaining the access:

1. If an email address was configured then click in the AdminCenter login window the link "Forgotten username or password?". Then instructions will be sent to this email address to enable the access again.
or
2. The system administrator / operator of the provider may set the login data again

Used Language in the AdminCenter GUI

The to use language of the AdminCenter GUI can be configured.

Renew the Password Upon First Access

It can be defined if the user has to renew the password upon the first AdminCenter access.

Deblock an AdminCenter Account

If an AdminCenter account is blocked then this is displayed with a selected box. By clicking the button [Deblock] it can be deblocked.

Limitation of the IP Subnet for the AdminCenter Access

Limitation of the IP Subnet for the Access

With this feature it is possible to define an IP subnet where the user is allowed to access this AdminCenter account.

The IP subnet is defined with the parameter "Network" . Several comma separated IP subnets are possible.
Example:

172.1.1.0/24,192.168.10.0/24

Limitation of the IP Subnets with an Access Profile

With this feature it is possible to define a set of IP subnets where the user is allowed to access this AdminCenter account.

The provider prepares the available "Access Profiles" . Check with the provider which IP subnets are associated with an access profile.

Configuration

Where to Configure this Feature

As vPBX administrator:

→ Tab "PBX"

→ Tab "Web"

Parameter Configuration

Parameter: Username

Description:	The actual username is displayed.	
	Note	The provider?s system administrator/operator can configure the user name.
Configuration:	Configuration String: ◇ Any string	
Default:	None	
Version:	AdminCenter V5.7	

Parameter: Current password

Description:	At a change of the password insert here the actual valid password!	
Configuration:	Configuration String: ◇ Any string	
Default:	None	
Version:	AdminCenter V5.7	

Parameter: New Password

Description:	At a change of the password insert here the new password!	
	Note	Follow the instructions on secure passwords!

Configuration:	Configuration String: ◇ Any string
Default:	None
Version:	AdminCenter V5.7

Parameter: Confirm new password

Description:	At a change of the password validate here the new password!
Configuration:	Configuration String: ◇ Any string
Default:	None
Version:	AdminCenter V5.7

Parameter: Username

Description:	Defines the AdminCenter account username for this vPBX
	Note This parameter is accessible for the provider?s system administrator/operator only.
Configuration:	Configuration String: ◇ Any string
Default:	Actual username
Version:	AdminCenter V5.7

Parameter: Password

Description:	Defines the AdminCenter account password for this vPBX
	Note This parameter is accessible for the provider?s system administrator/operator only.
	Note Follow the instructions on secure passwords!
Configuration:	Configuration String: ◇ Any string
Default:	None
Version:	AdminCenter V5.7

Parameter: Renew Password

Description:	Defines that the user has to renew its password upon the first login.
Configuration:	Selection Button: <input checked="" type="checkbox"/> Activated - <input type="checkbox"/> Not activated
Default:	Not activated
Version:	AdminCenter V6.2

Parameter: Language

Description:	Defines the used language in the AdminCenter GUI for this account.
Configuration:	Selection Menu: All available languages are listed
Default:	
Version:	AdminCenter V5.7

Parameter: Email

Description:	Defines the email address to which information will be sent how to reactivate the access to the AdminCenter account.
Configuration:	Email Address Configuration String: ◇ None : No email notification ◇ Email address
Default:	None
Version:	AdminCenter V5.7