

AdminCenter Account for the vPBX Administrator

Introduzione

Here the AdminCenter Login of the vPBX administrator is managed and configured:

- ◊ User name and password
- ◊ Language used the AdminCenter GUI
- ◊ Email address where instructions can be send for recovering the login if the current login credential are lost or forgotten
- ◊ Define if the password has to be renewed upon the first access by the user
- ◊ Unblock a blocked account
- ◊ Defining from which IP subnet a user is allowed to access its AdminCenter account
- ◊ Defining an Access Profile which contains a list allowed IP subnets where IP subnet a user is allowed to access its AdminCenter account

Contents

- 1 The AdminCenter Account for the vPBX Administrator
 - ◊ 1.1 The Login Credentials of the vPBX Administrator
 - ◊ 1.2 Procedure in Case of Loss of the Login Credentials
 - ◊ 1.3 Used Language in the AdminCenter GUI
 - ◊ 1.4 Renew the Password Upon First Access
 - ◊ 1.5 Unblock an AdminCenter Account
- 2 Limitation of the IP Subnet for the AdminCenter Access
 - ◊ 2.1 Limitation of the IP Subnet for the Access
 - ◊ 2.2 Limitation of the IP Subnets with an Access Profile
- 3 Configuration
 - ◊ 3.1 Where to Configure this Feature
 - ◊ 3.2 Parameter Configuration
 - ◊ 3.2.1 Parametro: Username
 - ◊ 3.2.2 Parametro: Current password
 - ◊ 3.2.3 Parametro: New Password
 - ◊ 3.2.4 Parametro: Confirm new password
 - ◊ 3.2.5 Parametro: Username
 - ◊ 3.2.6 Parametro: Password
 - ◊ 3.2.7 Parametro: Renew Password
 - ◊ 3.2.8 Parametro: Language
 - ◊ 3.2.9 Parametro: Email

The AdminCenter Account for the vPBX Administrator

The Login Credentials of the vPBX Administrator

The vPBX administrator can configure the password for its AdminCenter user account. The username can only be changed by the system administrator/operator of the provider.

An email address can be configured where instructions will be sent for recovering the login.

Procedure in Case of Loss of the Login Credentials

If login details are lost then the following procedures are possible for regaining the access:

1. If an email address was configured then click in the AdminCenter login window the link "Forgotten username or password?". Then instructions will be sent to this email address to enable the access again.
or
2. The system administrator / operator of the provider may set the login data again

Used Language in the AdminCenter GUI

The to use language of the AdminCenter GUI can be configured.

Renew the Password Upon First Access

It can be defined if the user has to renew the password upon the first AdminCenter access.

Deblock an AdminCenter Account

If an AdminCenter account is blocked then this is displayed with a selected box. By clicking the button [Deblock] it can be deblocked.

Limitation of the IP Subnet for the AdminCenter Access

Limitation of the IP Subnet for the Access

With this feature it is possible to define an IP subnet where the user is allowed to access this AdminCenter account.

The IP subnet is defined with the parameter "Network" . Several comma separated IP subnets are possible.
Example:

172.1.1.0/24,192.168.10.0/24

Limitation of the IP Subnets with an Access Profile

With this feature it is possible to define a set of IP subnets where the user is allowed to access this AdminCenter account.

The provider prepares the available "Access Profiles" . Check with the provider which IP subnets are associated with an access profile.

Configuration

Where to Configure this Feature

As vPBX administrator:

→ Tab "PBX"

→ Tab "Web"

Parameter Configuration

Parametro: Username

Descrizione:	The actual username is displayed.
	Nota The provider?s system administrator/operator can configure the user name.
Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	None
Versione:	AdminCenter V5.7

Parametro: Current password

Descrizione:	At a change of the password insert here the actual valid password!
Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	None
Versione:	AdminCenter V5.7

Parametro: New Password

Descrizione:	At a change of the password insert here the new password!
	Nota Follow the instructions on secure passwords!

Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	None
Versione:	AdminCenter V5.7

Parametro: Confirm new password

Descrizione:	At a change of the password validate here the new password!
Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	None
Versione:	AdminCenter V5.7

Parametro: Username

Descrizione:	Defines the AdminCenter account username for this vPBX
	<div>Nota</div> This parameter is accessible for the provider?s system administrator/operator only.
Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	Actual username
Versione:	AdminCenter V5.7

Parametro: Password

Descrizione:	Defines the AdminCenter account password for this vPBX
	<div>Nota</div> This parameter is accessible for the provider?s system administrator/operator only.
	<div>Nota</div> Follow the instructions on secure passwords!
Configurazione:	Stringa di configurazione: ◇ Any string
Predefinito:	None
Versione:	AdminCenter V5.7

Parametro: Renew Password

Descrizione:	Defines that the user has to renew its password upon the first login.
Configurazione:	Pulsante di scelta: <input checked="" type="checkbox"/> Attivato - <input type="checkbox"/> Non attivato
Predefinito:	Not activated
Versione:	AdminCenter V6.2

Parametro: Language

Descrizione:	Defines the used language in the AdminCenter GUI for this account.
Configurazione:	Menu di scelta: All available languages are listed
Predefinito:	
Versione:	AdminCenter V5.7

Parametro: Email

Descrizione:	Defines the email address to which information will be sent how to reactivate the access to the AdminCenter account.
Configurazione:	Email Address Stringa di configurazione: ◇ None : No email notification ◇ Email address
Predefinito:	None
Versione:	AdminCenter V5.7